



# MTR138-00GNW

## Mission Transceiver Remote

Rugged remote-mount radio solution for special-role and multi-mission platforms.

### Highlights

- **Easily** integrated for tactical roles, upgrades, or obsolescence management
- **Suitable** replacement for legacy VHF remote-mount radios
- **Integration** ability with glass cockpit applications

Covers VHF-FM frequency band from 138MHz to 174MHz



128 channels, including 2 programmable guard receiver channels

12.5kHz/25kHz channel bandwidths, selectable per channel

## MTR138-000GNW Features

MTR138-000GNW features an agile 10W main transceiver and a synthesized guard receiver, and was developed in consultation with emergency response agencies and aircraft manufacturers to produce a versatile and reliable special-mission radio.

This flexible radio solution boasts the most up-to-date advancements in analog radio technology in a lightweight, compact, and economical package. MTR138-000GNW is easily integrated for tactical roles, upgrades, or obsolescence management.

- A narrowband/wideband remote-mount transceiver
- Synthesized guard receiver
- High (10W) & Low (1W) output power
- Scanning modes (List, Priority, and List+Priority)
- Transceiver control handled through an RS-422 interface bus and discrete signals
- Provides sub-audible signaling, (CTCSS/CDCSS) capability with standard and extended tone encoding and decoding
- Tested to TIA-603-E
- DO-160G qualified

## Specifications

### MTR138-000GNW MECHANICAL SPECS

Height	4.80"
Width	2.30"
Length	10.35"
Weight	4.30 LB (MAX)

For more details, please email:  
[products@aem-corp.com](mailto:products@aem-corp.com)  
and see Installation & Operation  
manuals on our website:  
[aem-corp.com](http://aem-corp.com)

*LEADING  
BY DESIGN*